

Pulley Ratio Chart

The pulley ratio is the diameter of the crankshaft pulley divided by diameter of the alternator pulley. Multiply that number times the engine RPM to get the alternator rotor RPM.

For instance, a 6-inch crankshaft pulley and a 2.3-inch alternator pulley equals a pulley ratio of 2.61. 2.61 times an engine speed of 700 RPM equals 1827 rotor RPM.

Pulley Ratio Chart					
Alternator Pulley Diameter	Crankshaft Pulley Diameter				
	6.0"	6.5"	7.0"	7.5"	8.0"
1.9" (PA-4008*)	3.16	3.42	3.68	3.95	4.21
2.0" (PX-1353, PX-13468*)	3	3.25	3.5	3.75	4
2.2" (PX-1238, PA-4024*)	2.73	2.95	3.18	3.41	3.64
2.3" (PX-1128, PX-1129, PX-1130, PX-5570*)	2.61	2.83	3.04	3.26	3.48
2.35" (PX-1155*)	2.55	2.77	2.98	3.19	3.40
2.4"	2.5	2.71	2.92	3.13	3.33
2.5" (PX-1355*)	2.4	2.6	2.8	3	3.33
2.7"	2.22	2.41	2.59	2.78	2.96
3.0"	2.0	2.17	2.33	2.5	2.67
3.25"	1.85	2	2.15	2.31	2.46

* Numbers in parenthesis are PennTex Industries Pulley Part Numbers. These numbers are sometimes stamped on the front face of the pulley.

PERFORMANCE ENDURANCE AND SATISFACTION



**Manufacturers of
High Efficiency Alternators and
Mobile Electronic Devices.**

Corporate:
202 Plaza Drive
Manchester, PA 17345
Ph: 717/266-8762
Fax: 717/266-7803

www.penntexusa.com
Email: sales@penntexusa.com

Manufacturing:
7620 Flagstone Drive
Fort Worth, TX 76118
Ph: 817/590-2818
Toll Free: 877/590-7366
Fax: 817/590-0505

